

Heidenhain, Renishaw and MicroE XY Linear Encoder Installation

Congratulations on your choice of this option. The Tiger and MS2000 with XY linear encoders offers unparalleled accuracy and repeatability. The encoders used on MS2000 stages are optical devices with a count resolution of 10nm(with Heidenhain and Renishaw) and 2.5nm(MicroE). In order to give this superb performance, care must be taken in the handling of the encoders, scales, and stage.

Specifications

Heidenhain Spec	
Model	LIF 471
Scale Type	120mm long glass scale phase grating
Signal Period	4 μ m
Interpolation	\times 100
Resolution	10 nm
Accuracy	\pm 3 μ m over full travel range
Index	Center of travel range
Renishaw Spec	
Model	T-1000-30A w/ Ti2000 interpolator
Scale Type	RGSZ20 gold scale
Signal Period	10 μ m
Interpolation	\times 250
Resolution	10nm
Accuracy	\pm 3 μ m/m; \pm 0.75 μ m/60mm
Index	Near center of travel range
MicroE Spec	
Model	Mercury II 5800
Scale Type	Laser tape scale with 20 μ m grating period
Signal Period	20 μ m
Interpolation	\times 8000
Maximum speed	125mm/sec
Resolution	2.5 nm
Accuracy	\pm 30nm over 20 μ m travel, \pm 5 μ m over 1 meter travel
Index	Center of travel range

Installation

The linear encoders are installed at the factory on your stage. Careful alignment of the encoders has been already done for optimum performance. Please exercise care not to inadvertently bump the encoder heads or to smudge the scales when mounting or using the stage.

The encoder read heads and scales are embedded within the three stage plates. This protects the

encoders from contamination and provides for the most reliable operation.

Warnings



- DO NOT remove the encoder heads or the encoder scales from the stage unless you intend to do a complete realignment of the linear encoder.
- DO NOT make adjustments to the trim potentiometers on the encoder electronic modules.
- Please contact ASI if you believe that the linear encoder is not functioning properly.
- Install the stage on your microscope as described previously in this manual.

Connect the encoder read-heads to the correct connectors on the back of the MS2000, RM2000 and Tiger controller. The X and Y encoder cables (with attached electronics) are labeled and should be plugged into the corresponding labeled connectors on the controller.

Switch Settings

DIP SWITCH #3: This switch informs the firmware which encoder is in use. DIP Switch 3 should be DOWN for the linear encoders, UP to use the rotary encoders on the motors. The controller must be reset after changing DIP switch #3 for the firmware to notice the change.



Note: There are no dip-switches in Tiger system, axis is set in LE mode with [\[Addr#\]CCA X=1](#) for XY and [\[Addr#\]CCA X=3](#) for ZF. (You can switch back to rotary mode with X=2 for XY and X=4 for ZF)

Maintenance

The linear encoders are holographic devices that view an extended region of the scale at all times. This makes the encoder immune to miscounts due to dust or dirt. Nevertheless, if the scale becomes too dirty, inaccuracy and miscounts can result. Do not get fingerprints on the scale. If the scale becomes dirty, clean with a cotton swab moistened in alcohol. Allow all traces of the solvent to evaporate before using the stage.

Firmware Configuration and Features

The correct firmware configuration is installed at the factory. If the firmware is upgraded I the field, it may be necessary to correctly configure the controller for 10nm and 2.5nm resolution linear encoders. See the [CUSTOMA command](#) . After new firmware is installed, the following commands should be issued to the controller:

CCA X=21
RESET
10nm for Heidenhain and Renishaw encoders

CCA X=52
RESET
2.5nm for MicroE encoders

The index on the Linear encoders can be used as an absolute position reference. The user can access this feature using the [SI command](#) . The SI command causes the stage to seek the index location and set the absolute coordinate position of the index.

MicroE In-Field Alignment and Adjustment



Figure 1: a: Linear encoder alignment tool ATMI15000




Figure 1: b: On board software

If you wish to align the linear encoders to increase or decrease its resolution, it can be done thru the alignment too shown in figure a (purchased separately). The alignment tool will not only allow you to align the encoder but also to change the encoder resolution between 5um to 1.22nm and, adjust the programmable low pass filter which may reduce the maximum speed but improves noise and stability.

As always feel free to contact us thru support@asiimaging.com or call us at 1-541-461-8181 for further assistance.

[xystage](#), [manual](#), [common](#), [ms2000](#), [tiger](#), [Heidenhain](#), [microe](#), [Renishaw](#)

From:

<https://asiimaging.com/docs/> - **Applied Scientific Instrumentation**

Permanent link:

https://asiimaging.com/docs/heidenhain_xy_le

Last update: **2021/09/23 17:15**

